

CX-240MT (240W)

6 Zone Mixer Amplifier with Mp3 & Tuner & Bluetooth



Features:

- ✓ Public address (PA) 6 zone commercial mixer power amplifier.
- ✓ 19" rack mount amplifier of 2U height.
- ✓ Rated power output of 240W.
- ✓ 6 zone speaker outputs & 100V/70V/4-16 Ohms.
- ✓ Six zone speaker outputs with independent volume control.
- ✓ Built-in MP3 player by USB & SD, FM tuner & bluetooth.
- ✓ Mic1-3 inputs, Aux 1-2 inputs and line output.
- ✓ Microphone1 of VOX features of highest input priority.
- ✓ Volume control for Mic1-3 and Aux1-2, bass & treble and zone volume control on front panel.
- ✓ Power, signal, clip & protection LED indicator.
- ✓ Overload, short circuit and high temp protection.

Specification:

Model	CX-240MT
Description	6 Zone Mixer Amplifier with USB/FM & Bluetooth
Rated Power Output	240W
Speaker Output	6 Zone 100V outputs 100V/70V/4-16 Ohms
Input	Mic1-3: 600Ω, 3mV; Line1-2: 15kΩ, 250mV
Frequency Response	80-16KHz
THD	<0.1%
S/N Ratio	>70dB
Protection	High temp, short circuit, clip & overload protection
Power Supply	AC220V, 50-60Hz
Power Consumption	500W
Dimension	418(W)×318(D)×88(H)mm
Weight	13.68Kg

Rear Panel:

